

8-Channel Charge Amplifier Board with Programmable Digital Filtering & Simultaneous Sampling



Applications

- Flight test instrumentation
- Factory automation and process control
- Piezoelectric transducers, accelerometers, microphones, ...
- Research measurements, experiments and constant current

Features

- 8 channels per card
- Simultaneous sampling capability
- Programmable presample filtering
 - 32 Tap Finite-Impulse Response (FIR) filters
 - Approximates 12-pole Butterworth filter
 - Stop band attenuation of 85db
 - Analog anti-aliasing filter
 - Automatic adaptive filter
- Programmable input range
 - >10,000 settings from $\pm 11,000$ to $\pm 137\text{pC}$ full scale
- Programmable offset
- >1,000 Megohms input impedance (power on)
- $\pm 0.5\%$ system accuracy
- $\pm 35\text{VDC}$ overvoltage protection
- Compatible with WDAU-20XX operating to 20Mbps
- Microsoft Windows application software included

Description

The CAS-108D is an 8-channel plug-in signal conditioning board for use in TTC's EDAU-20XX and CDAU-20XX products. The board is intended for applications that require significant signal conditioning flexibility and simultaneous sampling capability. The board provides programmable digital presample filtering and user-programmable gain. The conditioned analog signal is digitized at up to 16-bit resolution for transmission in the system PCM output format.

Revision 09/28/2010

CAS-108D Datasheet

©2010 Teletronics Technology Corporation
 Specifications subject to change without notice.



Teletronics Technology Corporation
 15 Terry Drive, Newtown, PA 18940
 phone: 267.352.2020 fax: 267.352.2021 Sales@ttcdas.com

www.ttcdas.com