

4-Channel Signal Conditioning Module - Current and Voltage Excitation, Programmable Digital Filtering & Simultaneous Sampling



Applications

- Flight Test Instrumentation
- Factory Automation & Process Control
- Strain Gauges, Load Cells, Pressure Transducers, ...
- Research Measurements and Experiments

Features

- 4-Channels per Module
- Simultaneous Sampling Capability
- Programmable Digital FIR or IIR Presample Filtering
 - Software selected FIR filters: 120, 90, 60 and 40 Taps
 - 120 Tap FIR filter provides comparable response to 12- pole Butterworth Filter
 - Software selected IIR filters: 6-pole and 8-pole Butterworth, 6-pole Bessel and 6-pole Chebyshev
 - Automatic adaptive filter based on format sample rate
 - Analog anti-aliasing filter
- Constant voltage and fixed constant current excitation
 - Constant current excitation referenced to analog common to allow use of non-isolated transducers
- Programmable Gain and Offset
- AC and DC input coupling
- Zero Calibration
- ZIN >5M Ω (power on), >2 M Ω (power off)
- $\pm 0.25\%$ System Accuracy (Auto Cal Enabled)
- $\pm 0.5\%$ System Accuracy (Auto Cal Disabled)
- Automatic parasitic offset correction on power up and ZCAL. This feature can be disabled.
- $\pm 35\text{VDC}$ Overvoltage Protection
- Windows 95/98/NT/2000/XP/Vista Software Included

Description

The MSCD-604D is a 4-channel plug-in signal-conditioning module for use in TTC's MEDAU/MCDAU/MWDAU-2000 products. The module is intended for applications that require significant signal conditioning flexibility and/or simultaneous sampling capability. The module provides AC and DC input coupling, constant current and constant voltage excitation, programmable presample filtering, calibration, and user programmable gain and offset. FIR or IIR digital presample filtering may be selected. Each digital filter is phase locked to the channel format sample rate to maintain time correlation between the input signal and the PCM output. The filter can be set for 3, 4, 5, 6, 8 or 10 times oversampling (the filter -3dB point will be automatically set to the format sampling rate divided by the oversampling value). The current excitation is referenced to analog common, allowing use of non-isolated transducers. The conditioned analog signal is digitized at up to 16-bit resolution for transmission in the system PCM output format.

Revision 12/15/2008

MSCD-604D-3 Datasheet

©2008 Teletronics Technology Corporation

Specifications subject to change without notice.



Teletronics Technology Corporation

15 Terry Drive, Newtown, PA 18940

phone: 267.352.2020 fax: 267.352.2021 Sales@ttcdas.com

www.ttcdas.com